

## User Interface Basics

### What's in the Box?

1. RP 210E/220E in an ESD Bag
2. Cabinet Frame
3. Bag with fastening material
4. RJ45 Connector (IP rated)
5. Quick Installation Guide



### Caution!

Handle with care when opening the bag and installing the unit.

### Instrument Pages

Configurable Gauges and Bar-graphs.



### Select Page

Thumbnails for quick selection.



### Home & Alarm

buttons located at the upper right side of the panel.



### Start & Stop Engine

buttons located at the lower right side of the panel.

(N/A for RP 206E – no Start/Stop buttons)



### Alarm List

Red: Alarms/Shutdowns  
Yellow: Warnings  
White: Other messages  
Bold: Unconfirmed



### Menu

The Menu hierarchy. There may be several RP panels in a network but only one is in control. This is indicated by a star (★).



### For More Information:

For the latest updated information, please contact your local distributor or visit the Marine Pro 200 section of the Auto-Maskin web site: <http://www.auto-maskin.com>



# Marine Pro. 200

## Quick Installation Guide

RP 206E	P/N 1006478
RP 210E	P/N 1006476
	P/N 1006474
RP 220E	P/N 1006472

### Engine Remote Panel



- Hi res 5.7" touchscreen
- Ethernet communication for network and/or DCU engine panel
- 12V or 24V power supply
- USB Port
- IP66/56 rated
- Multilanguage support
- Configurable templates

### Measurements

Section	Width	Height	Depth	Unit
Size	162	130	67	mm
Cut out	155	123	90	mm

### Power Ratings

Section	Min	Typ.	Max	Unit
Power	8	12/24	32	VDC
Supply, Vcc	-	0.4	2	A

Max ripple 10% without exceeding Min and Max values.

### Rear side and Connectors



C1: Power, CAN, RIO, RIO Power  
 C2: AllFaults,  
 C3:  
 C4:

RJ45,  
 Ether-  
 net

### Responsibilities:

It is the sole responsibility of the installer to ensure that the installation work is carried out in a satisfactory manner and meet all applicable rules and regulations.

### Installation Steps

1. Remove the unit from the ESD Bag. Use the submitted Cabinet Frame and mount it in a suitable enclosure.
2. Attach the Power Supply connector (CON1) and make sure the power ratings are within product specifications.
3. Attach All Faults Relay (CON2).
4. Use additional sealed DT connectors and the submitted RJ45 Connector kit to ensure the IP rating.

A Connector Kit (P/N: 1006479) with four Deutsch DT-connectors, crimp sockets and sealing plugs is available. See the Installation Manual for further information.

### Note:

Auto-Maskin continuously upgrades its products and reserves the right to make changes and improvements without prior notice.

### Configuration Steps

At the first Power-Up the user will be guided through a Setup Wizard:

1. Language selection and your choice is valid through the rest of the procedure.
2. Network settings. Make sure to follow common network configuration practice and take care when several units need to operate within the same network.

PC Connection/Setup:

- Connect via Ethernet using a Net Browser
- From the Address Field in the Browser, type the IP-Address. Factory Default is **192.168.0.201**.
- Then log in to the unit. The Factory Default password is '1234'. (No User Name).

For further details and information, please see the Configuration Manual.

### Additional Documentation:

Please visit the Marine Pro 200 section of the Auto-Maskin web site for the following enhanced documentation:

- Installation Manual
- Configuration Manual
- User's Manual.

<http://www.auto-maskin.com>